


TYPE 6064
TRUSTWORTHY
MINIATURE HIGH SLOPE
R.F. PENTODE



The BRIMAR 6064 is an indirectly-heated high slope R.F. Pentode suitable for a wide variety of applications. It may be used as an R.F. or I.F. or video amplifier, as a limiter, or as a frequency changer at frequencies up to 100 Mc/s in conjunction with a suitable oscillator.

RATINGS

Heater Voltage	6.3	volts
Heater Current	0.3	amp.
Anode Voltage	275	volts max.
Anode Dissipation	2.75	watts max.
Screen (g_2) Voltage	275	volts max.
Screen Dissipation	0.8	watts max.
Heater to Cathode Potential	150	volts max.

OPERATING CHARACTERISTICS

(Suppressor Grid (g_3) connected to Cathode)

$V_h = 6.3$, $V_a = 250$, $V_{g_2} = 250$, $V_{g_1} = 0$, $V_{g_3} = 0$, $R_k = 160$ ohms, $C_k = 1,000 \mu F$.

	Min.	Bogey	Max.	
Anode Current	7.5	9.85	12.2	mA
Screen Current	1.8	2.6	3.4	mA
Mutual Conductance	6.0	7.62	9.25	mA/V
Inner Amplification Factor	60	75	89	
Anode Current at $V_{g_1} = -8$ V	100	μA

INTER-ELECTRODE CAPACITANCES*

Input	7.6	pF
Output	3.25	pF
Control Grid to Anode (max.)	0.01	pF

* With close-fitting shield connected to Cathode.

Type 6064 is a commercial equivalent to the CV4014.

