

VIDICONS

THOMSON - CSF has developed a wide range of SPECIAL VIDICONS to meet a great variety of television requirements :

INDUSTRIAL - MEDICAL - NUCLEAR

SCIENTIFIC - MILITARY - SLOW SCAN and DELAYED T.V.

Depending on their focus and deflection modes, their photoconductive layers or their structure, these SPECIAL VIDICONS include 3 families :

- VIDICONS WITH STANDARD PHOTOCONDUCTIVE LAYER having focus and deflection fully electrostatic or hybrid.
- VIDICONS WITH SPECIAL PHOTOCONDUCTIVE LAYER sensitive to IR, X or UV radiations.
- . SLOW SCAN AND STORAGE VIDICONS.

Furthermore, some VIDICONS can be equipped with F.O. face plate or with non browning radiation glass.

IDICONS WITH STANDARD PHOTOCONDUCTIVE LAYER

TH 9813

Magnetic deflection. Electrostatic focus. Usable in 40 mm diameter camera. Excellent uniformity of resolution and good raster linearity. High quality of general characteristics: high sensitivity, low lag. Designed for all applications in closed-circuit transistorized Television.

TH 9823


Electrostatic deflection and magnetic focus (when required by permanent magnet). High quality image due to magnetic focus and advantageous compactness due to electrostatic deflection. High resolution and excellent general performances. Especially intended for all Television system where small size and high quality of image are required.


TH 9824

Completely Electrostatic. Stability in operation and essential characteristics of image even in the case of high variations of electrode potential. Good resolution and raster linearity. High performances: sensitivity, lag. Ideally suited for all industrial Television requirements: very significant reduction in the dimensions and weight of the camera. Especially designed for applications where very small size is essential: Space Television, Military Television.

TH 9831

1 1/2" Vidicon. Magnetic deflection and electrostatic focus. Designed for professional equipments of very high quality. Very high performances. Excellent image quality and maximum resolution. Recommended for Black and White or color Broadcast Television, live scene pick up, and Television.





VIDICONS WITH SPECIAL PHOTOCONDUCTIVE LAYER

TH 9890


Magnetic focus and deflection. Highly sensitive to infrared radiation with the shold wavelength extending over 2 μm. Suitable both for Television operation in infrared light and for observation of hot body temperature.

TH 9894

Magnetic focus and deflection. X-ray sensitive Vidicon. Designed for non-destructive testing of components and assemblies Low lag layer capable of monitoring stationnary or in-motion phenomena. High resolution.

TH 9896

Magnetic focus and deflection. Designed for ultra-violet sensitive T.V. cameras. With quartz window and special target allowing for high sensitivity in U.V. region of spectrum. Recommended for use in industry (flame observation in daylight, gas injection in boilers) or in biology (U.V. television microscopy). . .




SLOW SCAN AND STORAGE VIDICONS

TH 9892

Magnetic focus and deflection. Designed for slow scan or delayed readout. Excellent light integration and storage characteristics. Suitable for slow scan pick-ups requiring high resolution such as for space application. Also suitable for narrow bandpass transmission (high signal to noise ratio) or very narrow bandpass (transmission of video information over telephone lines).


TH 9893

Magnetic focus and deflection. Storage Vidicon with readout performed in one T.V. frame. Storage time: several days. High resolution maintained after long storage time. Intended for delayed transmission of transient phenomena.



TH 9895

Magnetic focus and deflection. Storage Vidicon with non-destructive readout allowing for a 10 mm continuous reading. Excellent storage both in terms of resolution and duration of stored image. Intended for long duration or repeated readout of high speed events.



General Characteristics =

RENT .		0.15 A	TH 9813 - TH 9823 - TH 9824 - TH 9831
			TH 9892 - TH 9895 max at 550
TH 9831		Electrostatic focus - magnetic deflection	TH 9890 extending up to 2400
			TH 9892 max at 440
		Electrostatic focus and deflection	TH 9894 X - Ray sensitive
TH 9892	- TH 9893		TH 9896 max at 400
TH 9892		Magnetic focus and deflection	TH 9894

Electrical Operation Modes

SCANNED AREA					
TH 9813 - TH	1 9823 - TH	9824 - TH	9890		
TH 9892 - TH	I 9893 - TH	1 9894 - TH	9895		
TH 9896				12.7 x 9.5	mm
TH 9831 .				20.4 x 15.2	mm
ILLUMINATION				See light transfer curves.	
TEMPERATURE				25° ± 5°	С
FOCUS					
TH 9813 - TH	I 9824 - TH	9831 .		Vg3 # 0.3 Vg4	
TH 9823 .				Coil or permanent magnet	
TH 9890 - TH	I 9892 - TH	9893 - TH	9894		
TH 9895 - TH	1 9896 .			Focus coil	
ALIGNMENT				c oil	

TH 9813	3 - TH	9823	- TH	98	324 - T	H 9890						
TH 9892	- TH	9893	- TH	98	94 - T	H 9896				. 0	.2	μΑ
TH 9895	,								·	. 0	.1	μΑ
TH 9831							., ., .,			. 0	.6	μΑ
ELECTRODE	VOLT	TAGE	s		Po				w		de	
						Voltage				Voltage		
TH 9813	3				Vg5		500	٧	Vg4		300	٧
TH 9823	3				Vg5	450 to	600	٧	Vg4	300 to	400	٧
TH 9824					Vg5	500 to	600	٧	Vg4		300	٧
TH 9831					Vg5	1400 to	1500	V	Vg4	800 to 1	000	٧
TH 9890) .				Vg4	250 to	300	٧	Vg3	250 to	300	٧
TH 9892	2				Vg4		450	٧	Vg3		300	٧
TH 9893	3 - TH	9895			Vg4		400	٧	Vg3		300	٧
TH 9894					Vg4		750	٧	Vg3		450	V
					Vg4	400 to	450	V	Vg3	280 to	300	٧
	TH 9892 TH 9813 ELECTRODE TH 9813 TH 9823 TH 9824 TH 9831 TH 9894 TH 9895 TH 9895 TH 9895	TH 9892 · TH TH 9895 TH 9831 · ELECTRODE VOL* TH 9813 · TH 9823 · TH 9824 · TH 9831 · TH 9891 · TH 9890 · TH 9893 · TH TH 9894 · TH 9894 ·	TH 9892 - TH 9893 TH 9895	TH 9892 - TH 9893 - TH TH 9895 TH 9831	TH 9892 - TH 9893 - TH 98 TH 9895 TH 9831	TH 9892 - TH 9893 - TH 9894 - T TH 9895	TH 9895 TH 9831 ELECTRODE VOLTAGES Post acceler Voltage TH 9813 Vg5 TH 9823 Vg5 450 to TH 9824 Vg5 500 to TH 9831 Vg5 1400 to TH 9890 Vg4 TH 9892 Vg4 TH 9893 - TH 9895 Vg4 TH 9894 Vg4 TH 9894 Vg4 TH 9894 Vg4 TH 9894 Vg4 TH 9895	TH 9892 - TH 9893 - TH 9894 - TH 9896	TH 9892 · TH 9893 · TH 9894 · TH 9896 ·	TH 9892 - TH 9893 - TH 9894 - TH 9896	TH 9892 TH 9893 TH 9894 TH 9896 O TH 9895 O TH 9831 O ELECTRODE VOLTAGES Post acceleration Voltage Voltage TH 9813 Vg5 500 V Vg4 S00 to 600 V Vg4 S00 to 1 TH 9824 Vg5 500 to 600 V Vg4 TH 9831 Vg5 1400 to 1500 V Vg4 S00 to 1 TH 9890 Vg4 250 to 300 V Vg3 Z50 to 500 TH 9892 Vg4 S00 to 1 TH 9892 Vg4 S00 V Vg3 TH 9893 TH 9895 Vg4 S00 V Vg3 S00 to 1 TH 9894 Vg4 S00 V Vg3 S00 to 1 TH 9895 Vg4 S00 V Vg3 S00 TH 9896 Vg4 S00 V Vg3 S00 TH 9897 Vg4 S00 TH 9897	TH 9892 TH 9893 TH 9894 TH 9896

Typical Operations

	TH 9813					
TI (1915) BOTO O TOTO CONTRACTOR OF THE CONTRACT	H 9823 - TH 9824	TH 9831	TH 9890	TH 9892	TH 9894	TH 9896
AVERAGE SENSITIVITY						
Face plate illumination	10 lux	10 lux	 10 I.R. lux	 1 lux/s	 100 R/mn	. 0.5 μw
Target voltage	20 to 50 V	20 to 50 V	20 to 100 V	 30 V	 50 V	10 to 20 \
Dark current	20 nA	20 nA	 20 nA	 0.6 nA	 2 nA	. 05 nA
Signal current	200 nA	350 nA	 120 nA	 20 nA	 100 nA	 . 50 nA
				(ti = 1s)		
LAG						
Residual after 60 ms	. 20%	. 20% .	 45% .	 25% .	 	
Average gamma	. 0.65	. 0.65 .	 0.65	 0.9	 0.9 .	0.9

Particular Performances

AMETER	DEFLECTION (for electrode voltages defined in Electrical Operation Modes)
TH 9813 - TH 9823	TH 9813 Requires power 3 to 4 times less than TH 9812 (Magnetic focus) TH 9831 Requires power 3 to 4 times less than TH 9830 (Magnetic focus)
TH 9831	VIDICON+CAMERA ESTIMATED WEIGHT
NGTH See mechanical characteristics	TH 9813
cus	TH 9824
TH 9813 - TH 9824 - TH 9831 Negligible energy	TH 9831

lectrical norma	al m	nod	e)														(Cen	ter	lin	nitir	ng resolution	(T.)	٧.١	ines	5)					- 1	Per	cer	ntaç	ge o	of r	nodu	lation at 4	00 T.V. lin
TH 9813	3									٠.		٠.										650						٠.								· .		25	
TH 9823	3				. "		 ٠.			٠.	٠.					- 1						800						٠.										40	
TH 9824	4		. :							٠.	· .	٠.										450																15	
TH 9831	1							٠.	٠.													1000						٠.										60	
TH 9890	0														-			Z				550								1		i.						40	
TH 9894	4						· .															35 lp/mm																	
TH 9896	6			 			 	· ·			٠.			1.								800													٠.			40	
TH 9892	2			 			 · ·	٠.			٠.			100								800					,		٠						1,0			40	
TH 9893	3			 		. :								١.								600						١.				. "		٠.,		1.			
TH 9895	5							٠.					٠.									600													1.				

3.2 mm

Ø 6.75 mm.

max


TH C	9813 -	тн	0824	TH	9890	TH	0802	TH	0803					
	9894 -						3032					max	165	mı
THS									: :	•		max	112	m
TH 9												max	_	m
DIAMETE	R B) (se	e dra	w ing										
TH 9	813 -	TH	9824	- TH	9890	- TH	9892	- TH	9893					
TH 9	9894 -	TH	9895	- TH	9896	- TH	9823					max	26.7	m
TH 9	9831		•									max	38.5	m
RECTANO	BULA	R IM	AGE	МА	хіми	M DI	AGON	IAL						
TH 9	9813 -	TH	9823	- TH	9824	- TH	9890	- TH	9892					
TH 9	893 -	TH	9894	- TH	9895	- TH	9896				· .		17	m
	9831												25.4	m
THE														
	APPR	DXIN	MATE											
WEIGHT	APPR			- TH	9824	- TH	9890	- TH	9892					
WEIGHT .	9813 -	тн	9823						9892				60	g
WEIGHT .	9813 - 9893 -	TH TH	9823 9894	- TH	9895	- TH	9896						60 120	

393
Metox n° 30.250 Cinch n° 133-98-11-015
Cinch n° 203-62-13 031 or equivalent Metox
E.F. Johnson C° n° 124 311.100 or equivalent Metox
Alden n° 208 - SPEC or equivalent Metox
S
deflection and alignment assembly Gerhard BV 150/41 Cleveland VYA 300 Celco TV 348-S450/352-F215-A280
deflection and alignment assembly Cleveland 15 VYA 333 Celco HV 356-S500/330 A280
deflection and focus assembly Gerhard BV 200-1K1 alignment coil Gerhard BV 80/3 deflection-focus-alignment assembly Cleveland VYFA-355 2 Celco BV 232-S500/300-F240-A283

OUTLINE DRAWING

TH 9813

Base: Ditetrar 8 pins JEDEC E8-11



Heater

Electrode g1

Electrode g3 Electrode g5

Electrode g2

Electrode g4

Cathode

Heater


Flange : target

TH 9823

BASING DIAGRAMS (bottom

view)

Base : Ditetrar 11 pins JEDEC E11-22




- Heater Cathode
- 3 -D1 - Deflector
- D4 Deflector
- 5 -Electrode g3
- C -D2 - Deflector
- D3 Deflector 7 -8 -
 - Electrode g2
- g -Electrode g4
- 10 Electrode g1
- 11 Heater

Flange : target

TH 9824

Base: Ditetrar 13 pins JEDEC E8-13



D1 - Horizontal deflector

Electrode g2

Electrode g4

D4 - Vertical deflector

Electrode g1

Electrode g3

Internal connection

D2 - Horizontal deflector 9 -

10 -Electrode g5

11 -Cathode


12 -D3 - Vertical deflector

Heater

Flange: target

TH 9831

Base: Super Ditetrar 8 pins JEDEC E8-78




- Heater
- Electrode g1
- Electrode g3
- Electrode g5
- Electrode g2
- Electrode g4 6 -
- Cathode
- 8 Heater

Flange: target

TH 9890

Base : Ditetrar 8 pins JEDEC E8-11



Heater

Electrode g1 3 -

Internal connection

Internal connection 4 -


5 -Electrode q2

Electrodes g3 g4 6 -

Cathode

8 - Heater Flange: target

TH 9892 - TH 9893 - TH 9894 TH 9895 - TH 9896



Base: Ditetrar 8 pins JEDEC E8-11

1 - Heater

Electrode g1

3 - Electrode g4

Internal connection

5 - Electrode g2

6 - Electrode g3

Cathode

8 - Heater

Flange : target