INSTRUMENT CATHODE-RAY TUBE

- 12cm diagonal rectangular flat face
- domed mesh post-deflection acceleration
- high precision by permanent magnetic correction system
- low heater power consumption
- very high brightness
- for portable oscilloscopes with up to 50 MHz bandwidth and read-out devices

| QUICK REFERENCE DATA | TOICK | KEF | FHFV | ICE | DA | ΓÆ |
|----------------------|-------|-----|------|-----|----|----|
|----------------------|-------|-----|------|-----|----|----|

| V ₉₇₍₄₎ | 10 kV |
|----------------------------------|-----------------------------------|
| V _{g 2,4} | 1 kV |
| | 80 mm x 64 mm |
| M _x M _y | 12 V/cm · 7.5 V/cm |
| | V _{g 2,4} M _x |

| OPTICAL DATA | | | |
|---|--|-------------------------|--|
| Screen type colour persistence | metal backed phosphor GH (P31) green medium short | | |
| Useful screen area | | ≥82 mm x 66 mm (note 1) | |
| Useful scan area | | ≥80 mm x 64 mm | |
| Internal graticule | | type 119 (see Fig.4) | |
| HEATING | | | |
| Indirect by AC or DC * | | | |
| Heater voltage | V_{f} | 6.3 V | |
| Heater current | I, | 0.1 A | |
| Heating time to attain 10% of the cathode current at equilibrium conditions | | approx. 7 s | |

^{*} not to be connected in series with other tubes.

MECHANICAL DATA

Dimensions and connections (see also outline drawings)

Overall length (socket included)

Faceplate dimensions

Net mass (including trace rotation coil)

Base

7 25/5

max. 256 mm

 $98 \pm 0.5 \text{ mm } \times 82 \pm 0.5 \text{ mm}$

approx. 700 g

12 pin, all glass JEDEC B12-246

Mounting

The tube can be mounted in any position. It must not be supported by the socket and not by the base region alone. The reference points on adjoining edges of the faceplate (see Fig.4) enable the tube to be positioned accurately in the front panel, with optimum alignment of the internal graticule with respect to the bezel.

Accessories

Socket with solder tags

Socket with printed wiring pins

Final accelerator contact connector

Mu metal shield

type 55594

type 55595

type 55569/55597

to be established

FOCUSING

DEFLECTION

x plates

y plates

electrostatic

double electrostatic

symmetrical

symmetrical

CAPACITANCES *

| x ₁ to all other elements except x ₂ | C _{x1(x2)} | 3.7 pF |
|--|----------------------|-------------------|
| x ₂ to all other elements except x ₁ | $C_{x2(x1)}$ | 3.7 pF |
| y₁ to all other elements except y₂ | $C_{y1(y2)}$ | 3 _. pF |
| y ₂ to all other elements except y ₁ | C _{yalx1} , | 3 pF |
| $\mathbf{x_1}$ to $\mathbf{x_2}$ | $C_{x_1x_2}$ | 1.3 pF |
| y_1 to y_2 | C _{y1y2} | 1 pF |
| Control grid to all other elements | C _{g1} | 6 pF |
| Cathode to all other elements | C _k | 3 pF |
| Focus electrode to all other elements | C _{es} | 5 pF |
| Final accelerator electrode to all other elements | C _{g7} | 340 pF |

^{*} Approximate values

DIMENSIONS AND CONNECTIONS

Dimensions in mm




Fig.1 Mechanical outlines.

- (1) Dimensions of faceplate only. The complete assembly of faceplate and cone (frit seal included) will pass through an opening of 101 mm x 85 mm (diagonal 125 mm).
- (2) The coil is fixed to the envelope with silicone rubber and adhesive tape.
- (3) The length of rotation coil connecting leads is min. 350 mm.
- (4) Reference points on faceplate for graticule alignment.
- (5) The centre of the final accelerator contact is situated within a square of 10 mm x 10 mm around the indicated position.




Fig.2 Pin arrangement, bottom view.




Fig.3 Electrode configuration.

Internal graticule

The internal graticule is aligned with the faceplate by using the faceplate reference points, see Fig.4 and note 1.




Fig.4 Front view of the tube with internal graticule, type 119.

Reference points A1, A2 and A3 are for aligning the graticule with the faceplate ($|a1 - a2| \le 0.25$ mm). Line thickness = 0.16 mm; dot diameter = 0.36 mm; colour red.

TYPICAL OPERATION (voltages are with respect to the cathode)

| Conditions | | • | | |
|---|-----------------|--------------|------|---------|
| Final accelerator voltage | $V_{g7(\ell)}$ | 10 kV | • ,` | |
| Mean deflection plate potential | • | 1 kV | , . | note 2 |
| Shield voltage for optimum geometry | V_{95} | 1 kV | ", | лоte 3 |
| First accelerator and astigmatism control voltage | $V_{g2,4}$ | 1 kV | | note 3 |
| Focusing voltage | V _{d3} | 150 to 250 V | | Fig. 5. |

Outer conductive coating (m) and mu-metal shield to be earthed

Cut-off voltage for visual extinction of focused spot $-V_{g1}$

PERFORMANCE

| Horizontal deflection coefficient | $M_{\mathbf{x}}$. | 12 V/cm ± 10 % | |
|--|--------------------|-------------------------|--------|
| Vertical deflection coefficient | M _v | 7.5 V/cm ± 5 % | |
| Deviation of deflection linearity | | < 2% | note 4 |
| Geometry distortion | | | note 5 |
| Eccentricity of undeflected spot in horizontal direction in vertical direction | | < 4 mm < 2 mm | |
| Angle between x and y traces | • | 90° | note 2 |
| Angle between x-trace and x-axis of internal graticular | e | < 5° | note 6 |
| Luminance reduction with respect to screen centre x axis, outer graticule line y axis, outer graticule line any corner | | < 30% < 30% < 50% | , |
| Grid drive for 10 µA screen current | V _a | approx. 16 V | Fia 5 |
| Line width at 10 μ A at 25 μ A | l.w. | approx. 0.3 mm | Fig. 5 |

| LIMITING VALUES (Absolute maximum rating sys | stem) | • | , |
|---|-------------------------|--------------------------|--------|
| Final accelerator voltage | V _{g7(ℓ)} . | max. 18 kV | Fig. 6 |
| Shield voltage | V ₉₅ | max. 2,2 kV | |
| First accelerator and astigmatism control voltage | $V_{g2,4}$ | max. 2,2 kV | |
| Focusing electrode voltage | V^{g_3} | max. 2,2 kV | • |
| | | • • • | , |
| Control grid voltage | -V ₉₁ | max. 200 V min. O V | |
| Cathode to heater voltage | | | • |
| positive negative | V_{kf} - V_{kf} | max. 125 V max, 125 V | |
| Heater voltage | V, | max. 6.6 V | |
| | | min. 6.0 V | |
| | | п | • |
| Voltage between g _{4,5} and any deflection plate | / _{g4.g5.x,y,} | max. 500 V | h v |
| Grid drive, averaged over 1 ms | V _d | max. 25 V | |
| Screen dissipation | W_{ℓ} | max. 8 mW/cm² | , |
| Control grid circuit resistance | R_{a1} | max. 1 MΩ | |

NOTES

- 1. Because the frit seal is visible through the faceplate, and not necessarily aligned with the internal graticule, application of an external passe-partout with open area of max. 82 mm x 66 mm is recommended. The internal graticule is aligned with the faceplate by using the faceplate reference points (see Fig.4).
- 2. The deflection plates must be operated symmetrically: floating mean x- or y-potentials will result into non-uniform line width and geometry distortion. The mean x- and y-potentials should be equal; under this condition the tube will be within the specification without corrections for astigmatism and geometry.

The tube is adjusted by internal permanent magnetic elements for optimum geometry (orthogonality, trapezium, barrel/pin cushion), brightness uniformity, eccentricity of undeflected spot and astigmatism.

- 3. For some applications a mean x-potential up to 50 V positive with respect to mean y-potential is inevitable. In this case V_{g5} must be made equal to mean x-potential, and a range of 0 to 25 V with respect to mean y-potential will be required on $g_{2,4}$ for astigmatism correction. The circuit resistance for $V_{g2,4}$ should be < 10 k Ω .
- 4. The sensitivity at a deflection of less than 75 % of the useful scan will not differ from the sensitivity at a deflection of 25 % of the useful scan by more than the indicated value.
- 5. A graticule consisting of concentric rectangles of 80 x 64 mm and 78.6 x 62.8 mm is aligned with the internal graticule. With optimum trace rotation correction the edges of a raster will fall between these rectangles.
- 6. The tube has a trace rotation coil, fixed onto the lower cone part. The coil has a maximum resistance of 260 Ω at 80° C. The maximum required voltage is approx. 10 V for tube tolerances (\pm 5°) and earth magnetic field with reasonable shielding (\pm 2°).
- 7. Measured with the shrinking raster method in the centre of the screen under typical operating conditions, adjusted for optimum spot size.




Fig.5 Screen current (I_e) and focusing voltage (V_{g3}) as a function of grid drive voltage (V_d) at $V_{g2,g4,}=1000$ V; typical curves.





Fig.6 Isoexposure-rate limit curve for 0.5 mR/h, measured in accordance with EIA RS-502.

Raster: R../S3 RV-3-6-0/4
1997-08-01
Pag. 33 van 122



ZEEFDRUKKEN:

Ť

AFMETING

- 64 x 80 mm

LIJNDIKTE

 $-0.15 \pm 0.05 \text{ mm}$

LENGTE SCHAALVERDELINGSTREEPJES BASISLIJN - 2 mm LENGTE SCHAALVERDELINGSTREEPJES VERTICAAL - 3 mm SNELLE REFERENTIE - Speciaal type 10 x 10 schaaldelen