

# engineering data service

SYLVANIA 19XP4 19AVP4 19AXP4 19AYP4

#### **CHARACTERISTICS**

GENERAL DATA	
Focusing Method Electrostatic	
Deflection Method	
Deflection Angles (Approx.)	
Horizontal	
Diagonal	
Vertical	
Fluorescence	
Persistence Short to Medium	
Faceplate Gray Filter Glass	
Light Transmittance (Approx.) 78 Percent	
19 <b>AYP</b> 4 19 <b>XP</b> 4	
ELECTRICAL DATA 19AVP4	
Heater Voltage 6.3 6.3 Volts	
Heater Current $\pm 5\%$ 0.45 0.60 Ampere	
Heater Warm-up Time <sup>1</sup> 11 11 Seconds	
Direct Interelectrode Capacitances (Approx.)	
Cathode to All Other Electrodes	
Grid No. 1 to All Other Electrodes 6 $\mu\mu$ f External Conductive Coating to Anode <sup>2</sup> 1500 $\mu\mu$ f M	ax.
	in.
$1000~\mu\mu$ 1 Wi	111.
MECHANICAL DATA	
Minimum Useful Screen Dimensions (Maximum Assured)	
Height	
Width	
Diagonal	
Minimum Useful Screen Area	nes
Neck Length	
Bulb	
Bulb Contact (Recessed Small Cavity Cap)	
Base	
Basing 8HR	
Weight (Approx.)	

#### **RATINGS**


#### MAXIMUM RATINGS (Design Maximum Values)

	19 <b>AYP</b> 4			
Grid Drive Service <sup>3</sup>	19 <b>AVP</b> 4	19 <b>AXP</b> 4	19 <b>XP</b> 4	
Maximum Anode Voltage	23,000	20,000	20,000 Volts	dc
Minimum Anode Voltage				dc
Grid No. 4 Voltage (Focusing Elect	trode)	550 to	+1100 Volts	dc
Maximum Grid No. 2 Voltage		•	550 Volts	dc
Minimum Grid No. 2 Voltage		•	200 Volts	dc
Grid No. 1 Voltage				
Negative Bias Value			154 Volts	dc
Negative Peak Value		•	220 Volts	
Positive Bias Value			0 Volts	dc
Positive Peak Value			2 Volts	
Peak Heater-Cathode Voltage				
Heater Negative with Respect				
During Warm-up Period				
Exceed 15 Seconds			450 Volts	
After Equipment Warm-		•	200 Volts	
Heater Positive with Respect	to Cathode .	•	200 Volts	

### QUICK REFERENCE DATA

Television Picture Tube
19" Direct Viewed
Rectangular Glass Type
Spherical Faceplate
Gray Filter Glass
Aluminized Screen
Electrostatic Focus
114° Magnetic Deflection
1 ½" Neck Diameter
No Ion Trap
External Conductive Coating





## SYLVANIA ELECTRONIC TUBES

A Division of Sylvania Electric Products Inc.

### PICTURE TUBE OPERATIONS SENECA FALLS, NEW YORK

Prepared and Released By The TECHNICAL PUBLICATIONS SECTION EMPORIUM, PENNSYLVANIA

OCTOBER, 1961

PAGE 1 OF 3

File Under
TELEVISION PICTURE TUBES

#### MAXIMUM RATINGS (Design Maximum Values) Con't.

Cathode Drive Service <sup>4</sup>	19AVP4	19 <b>AXP</b> 4	19 <b>XP</b> 4
Maximum Anode Voltage	23,000	20,000	20,000 Volts
Minimum Anode Voltage	15,000	10,000	11,000 Volts
Grid No. 4 Voltage (Focusing Electrode)		400 t	o +1250 Volts
Maximum Grid No. 2 Voltage			700 Volts
Minimum Grid No. 2 Voltage			350 Volts
Cathode Voltage			
Positive Bias Value		•	154 Volts
Positive Peak Value			220 Volts
Negative Bias Value			0 Volts
Negative Peak Value			2 Volts
Peak Heater-Cathode Voltage			
Heater Negative with Respect to Cathode			
During Warm-up Period not to Exceed 15 Seconds			450 Volts
After Equipment Warm-up Period			200 Volts
Heater Positive with Respect to Cathode			200 Volts
YPICAL OPERATING CONDITIONS			10.1 WD (
TIGHT OF BRITTING COLUMN	19	AYP4	19 <b>AXP</b> 4

19AYP4

Grid Drive Service <sup>3</sup>	19A 1 P 4 19A V P 4	19XP4	
Anode Voltage	 . 20,000	16,000 Volts	dc
Grid No. 4 Voltage for Focus	 •	0 to 400 Volts	dc
Grid No. 2 Voltage		400 Volts	dc
Grid No. 1 Voltage Required for Cutoff <sup>5</sup>		–46 to –94 Volts	dc
Cathode Drive Service <sup>4</sup>	19 <b>AYP</b> 4 19 <b>AVP</b> 4	19 <b>AXP</b> 4 19 <b>XP</b> 4	
Cathode Bire Service	1/21 1 1 1	17/14	
	 	16,000 Volts	dc
Anode Voltage	 . 20,000	16,000 Volts 0 to 400 Volts	dc
<del></del>	 . 20,000	16,000 Volts	

#### CIRCUIT VALUES


#### NOTES:

- 1. Heater warm-up time is defined as the time required for the voltage across the heater to reach 80% of the rated heater voltage after applying four (4) times rated heater voltage to a circuit consisting of the tube heater in series with a resistance equal to three (3) times the rated heater voltage divided by the rated heater current.
- 2. External conductive coating must be grounded.
- 3. Voltages are positive with respect to cathode unless indicated otherwise.
- 4. Voltages are positive with respect to Grid No. 1 unless indicated otherwise.
- 5. Visual extinction of focused raster. For cutoff of the undeflected focused spot, the absolute value of the bias between cathode and grid will increase by about 5 volts.

#### **WARNING:**

X-ray radiation shielding may be necessary to protect against possible danger of personal injury from prolonged exposure at close range if this tube is operated at higher than the manufacturer's Maximum Rated Anode Voltage or 16,000 volts, whichever is less.

#### **OUTLINE**



#### **DIAGRAM NOTES:**

- 1. Reference Line is determined by plane C-C' of JEDEC No. 126 Reference Line Gauge, when the gauge is seated against the bulb.
- 2. Base Pin No. 4 aligns with horizontal centerline (A-A') within 30° and is on same side as anode contact, J1-21.